

SECTION 26 27 26

WIRING DEVICES

PART 1 - GENERAL

1.1 SUMMARY

A. Section Includes:

1. General-use switches, dimmer switches, and fan-speed controller switches.
2. General-grade single straight-blade receptacles.
3. Receptacles with arc-fault and ground-fault protective devices.
4. Locking receptacles.

1.2 ACTION SUBMITTALS

A. Product Data:

1. Toggle switches.
2. Dimmer switches.
3. Single straight-blade receptacles
4. Duplex straight-blade receptacles.
5. Receptacles with GFCI device.
6. Locking receptacles.

1.3 INFORMATIONAL SUBMITTALS

A. Manufacturers' Instructions: Record copy of official installation and testing instructions issued to Installer by manufacturer for the following:

1. Dimmers.
2. Single straight-blade receptacles.
3. Duplex straight-blade receptacles.
4. Duplex straight-blade receptacles with integral switching means.
5. Receptacles with GFCI device.
6. Locking receptacles.

PART 2 - PRODUCTS

2.1 RECEPTACLES WITH ARC-FAULT AND GROUND-FAULT PROTECTIVE DEVICES

A. General-Grade, Weather-Resistant, Tamper-Resistant Duplex Straight-Blade Receptacle with GFCI Device :

1. Regulatory Requirements:
 - a. Listed and labeled in accordance with NFPA 70, by qualified electrical testing laboratory recognized by authorities having jurisdiction, and marked for intended location and application.
2. Options:
 - a. Device Color: Ivory in accordance with NEMA WD 1 .
 - b. Configuration: Heavy-duty, NEMA 5-20R.
3. Accessories:
 - a. Cover Plate: 0.060 inch thick, high-impact thermoplastic (nylon) with smooth finish and color matching wiring device; from same manufacturer as wiring device.
 - b. Securing Screws for Cover Plate: Metal with head color matching wallplate finish.

PART 3 - EXECUTION

3.1 EXAMINATION

A. Receptacles:

1. Verify that receptacles to be procured and installed for Owner-furnished equipment are compatible with mating attachment plugs on equipment.

B. Cord Reels:

1. Examine roughing-in for cord reel mounting and power connections to verify actual locations of mounts and power connections before cord reel installation.
2. Examine walls, floors, and ceilings for suitable conditions where cord reel will be installed.
3. Proceed with installation only after unsatisfactory conditions have been corrected.

3.2 INSTALLATION OF SWITCHES

A. Comply with manufacturer's instructions.

B. Reference Standards:

1. Unless more stringent requirements are specified in Contract Documents or manufacturers' instructions, comply with installation instructions in NECA NEIS 130.
2. Mounting Heights: Unless otherwise indicated in Contract Documents, comply with mounting heights recommended in NECA NEIS 1.
3. Consult Architect for resolution of conflicting requirements.

C. Identification:

1. Identify cover or cover plate for device with panelboard identification and circuit number in accordance with Section 26 05 53 "Identification for Electrical Systems."
 - a. Mark cover or cover plate using hot, stamped, or engraved machine printing with black - filled lettering, and provide durable wire markers or tags inside device box or outlet box.

3.3 INSTALLATION OF STRAIGHT-BLADE RECEPTACLES

- A. Comply with manufacturer's instructions.
- B. Reference Standards:
 - 1. Unless more stringent requirements are specified in Contract Documents or manufacturers' instructions, comply with installation instructions in NECA NEIS 130.
 - 2. Mounting Heights: Unless otherwise indicated in Contract Documents, comply with mounting heights recommended in NECA NEIS 1.
 - 3. Receptacle Orientation: Unless otherwise indicated in Contract Documents, orient receptacle to match configuration diagram in NEMA WD 6.
 - 4. Consult Architect for resolution of conflicting requirements.
- C. Identification:
 - 1. Identify cover or cover plate for device with panelboard identification and circuit number in accordance with Section 26 05 53 "Identification for Electrical Systems."

3.4 INSTALLATION OF LOCKING RECEPTACLES

- A. Comply with manufacturer's instructions.
- B. Reference Standards:
 - 1. Unless more stringent requirements are specified in Contract Documents or manufacturers' instructions, comply with installation instructions in NECA NEIS 130.
 - 2. Mounting Heights: Unless otherwise indicated in Contract Documents, comply with mounting heights recommended in NECA NEIS 1.
 - 3. Receptacle Orientation: Unless otherwise indicated in Contract Documents, orient receptacle to match configuration diagram in NEMA WD 6.
 - 4. Consult Architect for resolution of conflicting requirements.
- C. Identification:
 - 1. Identify cover or cover plate for device with panelboard identification and circuit number in accordance with Section 26 05 53 "Identification for Electrical Systems."
 - a. Mark cover or cover plate using hot, stamped, or engraved machine printing with white - filled lettering, and provide durable wire markers or tags inside device box or outlet box.

3.5 PROTECTION

- A. Devices:
 - 1. Schedule and sequence installation to minimize risk of contamination of wires and cables, devices, device boxes, outlet boxes, covers, and cover plates by plaster, drywall joint compound, mortar, cement, concrete, dust, paint, and other materials.

2. After installation, protect wires and cables, devices, device boxes, outlet boxes, covers, and cover plates from construction activities. Remove and replace items that are contaminated, defaced, damaged, or otherwise caused to be unfit for use prior to acceptance by Owner.

B. Connectors, Cords, and Plugs:

1. After installation, protect connectors, cords, and plugs from construction activities. Remove and replace items that are contaminated, defaced, damaged, or otherwise caused to be unfit for use prior to acceptance by Owner.

END OF SECTION 26 27 26